



**11 OR 13 WATT G24 BASE LED LIGHT**



|                           |   |           |
|---------------------------|---|-----------|
| LED quantity:             | 45 /65  | SMD5050's |
| Light Color:              | Warm – Day – Cool White   |           |
| Color Temperature:        | 3000 / 4500 / 6500 K  |           |
| Bases Available:          | <b>E27,G24D-1,G24D-2,G24D-3,G24Q1,<br/>G24q-2,G24q-3,G24q-4</b>   |           |
| Operating Voltage A/C:    | 110 – 277   |           |
| Frequency:                | 50HZ – 60HZ   |           |
| Operating Temperature:    | -30°F to + 160°F  |           |
| CRI:                      | >75   |           |
| Total Current/Power used: | 0.11 Amps   |           |
| Power Used:               | <b>11-13 Watts (5W &amp; 8W avail)</b>  |           |
| Power Efficiency:         | >0.85   |           |
| Surface Brightness:       | 10,500 Lux  |           |
| Luminous Flux:            | 750 /1,050 Lm   |           |
| Electrical Standard:      | RoHS, CE  |           |
| Beam Angle of Each LED:   | 130°  |           |
| Lifetime of Lamp:         | 50,000 hours +  |           |
| IP:                       | 20  |           |
| Dimensions:               | 6.15" X 1.41" / 7.25" X 1.41"   |           |
| Weight:                   | 7 – 8.5 ounces  |           |
| Features:                 | <b>Rotating base, replaces 36-42W CFL,<br/>No ballast needed (remove/bypass),<br/>Minimum order -5 pieces</b> |           |

**Installation:**

**For retrofit, bypass incoming fixture voltage - wires (120 – 277 VOLTS A/C) directly to the lamp base, unless using a standard E27 Base. This should be done by qualified electrical professional. No modifications allowed to bulbs as this could cause damage to heat-sink, loosen electronics, and void warranty. Existing fixture socket may need to be adjusted. Do not look directly at light at close range – very bright. All Bravolight products are certified CE & RoHS.**